## How to set switches with isCOBOL

Author: Veryant Support

Saved From: <a href="http://support.veryant.com/support/phpkb/question.php?ID=339">http://support.veryant.com/support/phpkb/question.php?ID=339</a>

A common practice in COBOL programming is to manage switches to change the behavior of the program. In isCOBOL there are four ways to accomplish this task:

1. In your configuration file using the "iscobol.switches=" configuration variable

You can pass switches to your program from the configuration file. For instance:

```
iscobol.switches=1
will activate only switch 1,
   iscobol.switches=3
will activate only switch 3,
   iscobol.switches=1,3
will activate switchs 1 and 3
```

The runtime will set these switches when you pass the configuration file in your execution line. For instance:

iscrun -c switch.properties MAIN

## 2. In the command line using -J-D syntax

The configuration variable in #1 above can also be set in your command line by prefacing the variable with "-J-D". For instance, to run a program called "MAIN";

```
iscrun -J-Discobol.switches=1 MAIN
will activate only switch 1
  iscrun -J-Discobol.switches=3 MAIN
will activate only switch 3
  iscrun -J-Discobol.switches=1,3 MAIN
will activate switchs 1 and 3
```

2. Setting ';switches'; in the environment

Set the envrionment variable from a system shell. In this case, you would remove the "iscobol." from the variable. For instance, on Windows;

```
set switches=3
will activate only switch 3
   set switches=1, 3
will activate switchs 1 and 3
And in Linux, you would use the export command:
   export switches=1
will activate only switch 1
   export switches=3
will activate only switch 1
   export switches=1, 3
will activate switchs 1 and 3
```

With the switches set in the environment, you don';t need to pass them to the runtime from the command line, so your command line is simply:

```
set sw-2 to on
```

If you want to clear the switches at the end of the process, you can set the switches to blank or space. For example:

set SWITCHES=

Attached to this KB article is a .zip file containing two sample programs and a configuration file that show how to work with switches.

You can use them to test the 4 ways to set switches outlined above.

Unzip the files, and compile them with

iscc \*.cbl